What is claimed is:

1) A circuit capable to receive an input signal having a duty-cycle, comprising:

a first sampler capable to obtain a first edge value from the input signal responsive to an edge clock signal;

a second sampler capable to obtain a first data value from the input signal responsive to a data clock signal; and,

a duty-cycle-correction logic, coupled to the first and the second samplers, capable to generate a duty-cycle-correction signal that adjusts the edge clock to the duty-cycle of the input signal duty-cycle responsive to the first edge value and first data value.

2) The circuit of claim 1, wherein the data clock signal has an approximate 50% duty–cycle and is in quadrature with an adjusted edge clock signal.

3) The circuit of claim 1, further comprising:

a third sampler, coupled to the duty-cycle-correction logic, capable to obtain a second data value; and,

wherein the duty-cycle-correction logic is capable to generate the duty-cycle-correction signal responsive to the first data value, first edge value and second data value.

4) The circuit of claim 3, wherein the duty-cycle-correction logic comprises:

an evaluator circuit capable to generate an up signal or a down signal, responsive to the first data value, first edge value and second data value; and,

a duty-cycle clock integrator, coupled to the evaluator circuit, capable to generate the duty-cycle-correction signal responsive to the up or down signal.

5) The circuit of claim 4, further comprising:

a first phase comparator, coupled to the first sampler, capable to generate the data clock signal; and,

a second phase comparator, coupled to the first duty-cycle clock integrator and the second sampler, capable to generate the edge clock signal responsive to the duty-cycle-correction signal.

6) The circuit of claim 1, wherein the input signal is a double-data rate signal and the circuit is included in a double-data rate system.

7) The circuit of claim 1, wherein the circuit is included in a memory module coupled to a double-data rate bus.

8) A circuit capable to receive an input signal having a duty-cycle, comprising:

a first sampler capable to obtain a first edge value from the input signal responsive to an edge clock signal;

a second sampler capable to obtain a second edge value from the input signal responsive to the edge clock signal; and

a duty-cycle-correction logic, coupled to the first and the second samplers, capable to generate a duty-cycle-correction

signal that adjusts the edge clock to the duty-cycle of the input signal duty-cycle responsive to the first and second edge values.

9) The circuit of claim 8, wherein a data clock signal has an approximate 50% duty–cycle and is in quadrature with an adjusted edge clock signal.

10) The circuit of claim 8, wherein the duty-cycle-correction logic comprises:

an evaluator circuit capable to generate an up signal or a down signal, responsive to the first and second edge values; and,

a duty-cycle clock integrator, coupled to the evaluator circuit, capable to generate the duty-cycle-correction signal responsive to the up or down signal.

11) The circuit of claim 10, further comprising:

a first phase comparator, coupled to the duty-cycle clock integrator and the first and second samplers, capable to generate the edge clock signal responsive to the duty-cycle-correction signal.

12) The circuit of claim 8, wherein the input signal is a double-data rate signal and the circuit is included in a double-data rate system.

13) The circuit of claim 8, wherein the circuit is included in a memory module coupled to a double-data rate bus.

14) A circuit capable to receive an input signal having a duty-cycle, comprising:

a first sampler capable to obtain a first edge value from the input signal responsive to an edge clock signal;

a second sampler capable to obtain a second edge value from the input signal responsive to the edge clock signal;

a duty-cycle-correction logic, coupled to the first and the second samplers, capable to generate a duty-cycle-correction signal that adjusts the edge clock to the duty-cycle of the input signal responsive to the first and second edge values;

wherein the duty-cycle-correction logic includes,

an evaluator circuit, coupled to the first and second samplers, capable to generate an adjust signal, responsive to the first and second edge values;

a counter, coupled to the evaluator circuit, capable to output a count value responsive to the adjust signal;

a digital-to-analog-converter, coupled to the counter, capable to generate an analog offset signal responsive to the count signal; and,

a duty-cycle clock integrator, coupled to the digital-to-analog-converter, capable to generate the duty-cycle-correction signal responsive to the analog offset signal.

15) The circuit of claim 14, wherein a data clock signal has an approximate 50% duty–cycle and is in quadrature with an adjusted edge clock signal.

16) The circuit of claim 14, further comprising;

a digital filter coupled to first and second samplers and the evaluator circuit.

17) The circuit of claim 16, wherein the input signal is a coded input signal having an approximate same number of even and odd data transitions.

18) The circuit of claim 14, further comprising:

a first phase comparator, coupled to the duty-cycle clock integrator and the first and second samplers, capable to generate the edge clock signal responsive to the duty-cycle-correction signal.

19) The circuit of claim 14, wherein the input signal is a double-data rate signal and the circuit is included in a double-data rate system.

20) The circuit of claim 14, wherein the circuit is included in a memory module coupled to a double-data rate bus.

21) An apparatus, comprising:

a transmit circuit capable to transmit a serial signal having a duty-cycle;

a receive circuit, coupled to the transmit circuit, including

a first sampler capable to obtain a first edge value from the serial signal responsive to an edge clock signal;

a second sampler capable to obtain a first data value from the serial signal responsive to a data clock signal; and,

a duty-cycle-correction logic, coupled to the first and the second samplers, capable to generate a duty-cycle-correction signal that adjusts the edge clock signal to the duty-cycle of the serial signal duty-cycle responsive to the first edge value and first data value.

22) An apparatus, comprising:

a transmit circuit capable to transmit a serial signal having a duty-cycle; and,

a receive circuit, coupled to the transmit circuit, including

a first sampler capable to obtain a first edge value from the serial signal responsive to an edge clock signal;

a second sampler capable to obtain a second edge value from the serial signal responsive to the edge clock signal; and,

a duty-cycle-correction logic, coupled to the first and the second samplers, capable to generate a duty-cycle-correction signal that adjusts the edge clock to the duty-cycle of the serial signal duty-cycle responsive to the first and second edge values.

23) An apparatus, comprising:

a transmit circuit capable to transmit a serial signal having a duty-cycle; and,

a receive circuit, coupled to the transmit circuit, including,

a first sampler capable to obtain a first edge value from the serial signal responsive to an edge clock signal;

a second sampler capable to obtain a second edge value from the serial signal responsive to the edge clock signal;

a duty-cycle-correction logic, coupled to the first and the second samplers, capable to generate a duty-cycle-correction signal that adjusts the edge clock to the duty-cycle of the serial signal responsive to the first and second edge values;

wherein the duty-cycle-correction logic includes,

an evaluator circuit, coupled to the first and second samplers, capable to generate an adjust signal, responsive to the first and second edge values;

a counter, coupled to the evaluator circuit, capable to output a count value responsive to the adjust signal; and,

a digital-to-analog-converter, coupled to the counter, capable to generate the duty-cycle-correction signal responsive to the count signal.

24) A method, comprising the steps of:

receiving an input signal having a first duty-cycle;

sampling the input signal to obtain a plurality of edge values from the input signal responsive to an edge clock signal having a second duty-cycle; and,

adjusting the second duty-cycle of the edge clock to the first duty-cycle of the input signal responsive to the plurality of edge values.

25) The method of claim 24, further comprising the steps of:

sampling the input signal to obtain a plurality of data values from the input signal responsive to a data clock signal.

26) The method of claim 25, wherein the adjusting step includes adjusting the data clock signal to have an approximate 50% duty–cycle and be in quadrature with an adjusted edge clock signal.

27) A circuit capable to receive an input signal having a duty-cycle, comprising:

a sampler capable to obtain a plurality of edge values from the input signal responsive to an edge clock signal having a duty-cycle; and,

means, coupled to the sampler, for adjusting the edge clock signal duty-cycle to the input signal duty-cycle.